

# Super Mini Tower CSE-731i-300B

## Specifications

### Key Features

1. Mini-tower Chassis
2. 300W High-efficiency (80Plus, Bronze) Power Supply
3. Drive Bays: 2x 5.25" External, 4x 3.5" Internal, & 1x OEM optional 3.5" External Drive
4. **4x** I/O Expansion Slots
5. **2x** USB Front Access I/O
6. Rear 9cm PWM Fan w/ tool-less design and 1x optional Front exhaust 8cm Fan
7. Blue On/Off LED Power switch and 3 LED indicators
8. Quick-and-Easy design for installation: Tool-less Side Panels, Drive Bays, HDD Cage turns 90°, & Stamped Motherboard Support (no standoffs required)
9. Motherboard supported: Micro-ATX (9.6" x 9.6")
10. Kensington Lock Security to Safeguard the System



Mini-tower Chassis

### Processor Support

Supports Intel® & AMD processor motherboards

### Form Factor

Mini-Tower Chassis supports Micro-ATX motherboards, size 9.6" x 9.6"

### Expansion Slots

4x Full-height, Full-length I/O expansion slots

### Key Applications

Ideal chassis for home, office, or small entree level business use.

Various Tool-less designs enable quick-and-easy installation.

### Front Panel

Buttons

- Blue On/Off LED Power switch
- System Reset button

LEDs

- Power status LED
- Hard drive activity LED
- Network activity LED
- System overheat LED

### Drive Bays

Internal Bay 4x 3.5" Tool-less HDD trays

External Bay(s) 2x Standard 5.25" and 1x 3.5" drive bay (OEM option)

### Peripheral Drives

CD/DVD-ROM CD/DVD-ROM drive (optional)

### Power Supply

300W High-efficiency (80Plus, Bronze) Power Supply



### Cooling System

1x Rear 9cm PWM Fan w/ toolless design; 1x optional Front 8cm Cooling Fan

### Dimensions

W x H x D 7.25" (184mm) x 14.25" (362mm) x 16.75" (425mm)

For the most current product information, visit: [www.supermicro.com](http://www.supermicro.com)

12/22/2008